
Deako Smart Lighting - Integration Guide

Deako Smart Devices can be added to an Alarm.com ecosystem to include lighting automation as part of a smart home or business experience. Deako Smart Devices can be remotely controlled and automated using the Customer website and Customer app.

Deako lighting products have a unique modular plug-in design, so can upgrade customers to more advanced options easily, without the expense of an onsite electrician and high-voltage wiring.

Requirements

- Compatible mobile versions:
 - iOS device with firmware version 8.0+
 - Android device with firmware version 2.1+
 - Alarm.com mobile app version 4.10.4+
- Current versions of the Deako mobile app
- At least one Wi-Fi-enabled Deako Smart Device (e.g., Deako Connect, Deako second-gen Smart Switch, etc.)
- *Light & Thermostat Bundle*, or *Lights* service package add-on

Features

- Remote control and automate lights with rules, schedules, and Scenes

Note: The physical Scene buttons on Deako Scene Controller devices are only compatible with Deako Scenes. These devices can still be added to Alarm.com Scenes, but they must be run remotely.

- Sleek, modern look with screw-less faceplate
- Modular, plug-in design for easy upgrades (for more information, visit [Deako.com](https://deako.com))
- Fit into a variety of switch wiring setups
 - Single pole (two brass terminal screws and On/Off toggle; controls one fixture from a single location)
 - 3-way (three terminals; controls one fixture from two locations)
 - 4-way (four terminals; controls one fixture from three locations)

Integrate the Deako account to Alarm.com using the Add Device Portal

Use the Deako app login to add a Deako Smart Device to the Alarm.com account using the Add Device Portal in the Customer website or app.

For more information about how to enable the Add Device Portal, see [Add Device Portal](#).

Expand all

To add the Deako Smart Device using the Customer website: ^

1. Log in to the Customer website.
2. Click **Settings**.
3. Click **Manage Devices**.
4. Click **Add Device**.
5. Click **Lighting and Appliance Control**.
6. Click **Deako Smart Device**.
7. Click **Next** to proceed to sign in to add the device to the account.
8. The Deako account login appears. Click **Log in/Sign up** and then log in to the Deako account.
 - The option to *Sign in with Apple* is not a supported Alarm.com integration path. If you only use Apple login for the Deako app, invite another non-Apple user to your Deako profile, and use those login credentials to integrate the two platforms. For example, if you use 123@appleid, add a second user to your home 123@gmail, and use the 123@gmail credentials to connect Alarm.com and Deako together.
9. Select the Deako home profile to connect to the Alarm.com account.
 - Only one home can be connected per email address. When setting up two or more homes, use a different email address for each one. If you use the same email address for both homes, only the one that was added last will be integrated with Alarm.com.
10. Allow a few minutes for the connection to complete.
 - If the Alarm.com account has a compatible security panel, the Deako switches will automatically show up on the panel in less than an hour.

To access the Deako Smart Device using the Customer app: ^

1. Log in to the Customer app.
2. Tap ≡.
3. Tap **+ Add Device**.
4. Tap **Lighting and Appliance Control**.
5. Tap **Deako Smart Device**.
6. Tap **Next** to proceed to sign in to add the device to the account.
7. If a prompt asks for Alarm.com to use deako.com to sign in, tap **Continue**.
8. The Deako account login appears. Tap **Log in/Sign up** and then log in to the Deako account.
 - The option to *Sign in with Apple* is not a supported Alarm.com integration path. If you only use Apple login for the Deako app, invite another non-Apple user to your Deako profile, and use those login credentials to integrate the two platforms. For example, if you use 123@appleid, add a second user to your home 123@gmail, and use the 123@gmail credentials to connect Alarm.com and Deako together.
9. Select the Deako home profile to connect to the Alarm.com account.

- Only one home can be connected per email address. When setting up two or more homes, use a different email address for each one. If you use the same email address for both homes, only the one that was added last will be integrated with Alarm.com.
10. Allow a few minutes for the connection to complete.
- If the Alarm.com account has a compatible security panel, the Deako switches will automatically show up on the panel in less than an hour.